# ogosease

Logosease RG-004·RG-005 共通

基本的な使い方


Ver. 2.0

山形カシオ株式会社

# CASIO<sub>®</sub>

## 3. ご使用方法

が当たるようにセットしてください。





※骨伝導マイクの位置がずれていると、音声がうまく 伝わりません。耳珠前方の骨に密着させてください。

#### 目次

## 1. 各部の名称・同梱品

## 2. ご使用の前に

- ①充電確認
- ②落下防止用ストラップの取り付け ③ロゴシーズの取り付け
- 3. ご使用方法
- 装着
- ②送信・受信の切り替え ③話す・聞く
- ④電源を切る
- 4. お手入れ方法 5. 充電方法
- 6. 困ったときは

詳しい仕様やトラブルシューティングに関しては 付属の取扱説明書を必ずお読みください。

#### 〔各部名称〕

1.各部の名称・同梱品



アンテナ

母音を発声

もしくは

タッピング

送信モート

話す


話し終わる


3秒間無

もしくは

タッピング







#### 〔同梱品〕



- レギュレータを咥えたまま喋るには? ―



# で使用の前に、必ず充電してください。

## (充電方法は裏面5項参照)

2. ご使用の前に

ロゴシーズの水検知センサーを水で

ぬらすと、自動的に電源が入ります。

その後2秒間、LEDが点滅しますの

で、LED の色で充電状態を確認して

LED

①充電確認

ください。

#### 4. お手入れ方法

①一日のダイビングが終了したら必ず真水で洗い、

※洗剤等は使用しないでください。また、USB端子部の汚れは ブラシ等で清掃してください。



②乾いた布で拭き取りましょう。



# ストラップタイ ストラップ側

マスクストラップ右側のストラップタイをバックル

側に移動してください。ストラップ(本体側)を

ロゴシーズのストラップホルダーに取り付けます。

②落下防止用ストラップの取り付け

バックル

5. 充電方法



#### ③ロゴシーズの取り付け

6. 困ったときには

の項目をご確認ください。

■装着位置の確認 (送信側)

同梱のストラップ(マスクストラップ側)をご使用 のマスクストラップの右側に取り付けます。



## 🗙 間違った装着方法

左側に装着しないでください 本機は右側に装着してご使用 ください。

ロゴシーズのクリップをマスクストラップに取り

付けます。外れないように、クリップの奥までしっかり入れてください。



緑

満充電

青

ダイビング約1回分

の残量

赤

要充電

①USB ケーブルを充電スタンドと、パソコン(または 市販の USB-AC アダプタ)にそれぞれ接続して ください。



②ロゴシーズを充電スタンドにセットし、カチッと 音がするまで押し込みます。







正しい装着位置や方法は3項をご参照ください。

通信状態が悪い(音が聞き取りづらい)場合は、以下



★ 耳と被っている ★ 下がりすぎている

## ■使用環境の確認



★ 左右反対

★ 相手との間に岩などの障害物がある

#### ■本体の確認





★ アンテナに気泡が付着している ★ アンテナ前方に遮蔽物がある。







★本体に排気がぶつかっている

を右に傾けるなど、できるだけ排気が いらないようにして話してください

詳しい仕様やトラブルシューティングに関しては 付属の取扱説明書を必ずお読みください。



耳珠の前方の骨(あごの付け根)に、骨伝導マイク



## ②送信・受信切り替え

電源を ON すると、受信モードで起動します。 「いっ!」など母音を強く短く発声すると送信モード になります。

3秒間何も話さなければ受信モードに戻ります。 もしくは、本体側面を1度タッピング(軽く指で叩く こと)をして送信・受信の切り替えをします。





#### ③話す・聞く 〔通信の流れ〕

電源 ON はじめは必ず、付属の会話トレーニング シートを使って、レギュレータを咥えて 言葉を話すトレーニングをおこなって ください。 → 受信モード

骨伝導マイク

(音) ピ・ボッ

話せば話すほど、上達してゆきます。



#### ④電源を切る 電源は、水から出して1分経過すると自動的に

切れます。(「ピ・ピ・ピ・ピ ピー・ピー・ ピー・ピー」と音が鳴ります。)

海水や汚れを取りましょう。







## **BASIC INSTRUCTION**

Logosease RG-004 · RG-005 Ver. 2.0

YAMAGATA CASIO CO.,LTD.




bone - conduction

microphone

### 3. How to use

Set a bone conduction microphone as touching the bone in front of antilobium (base of jaw).





\* If the bone conduction microphone is set at the wrong position, sound will not be heard clearly at receiver's side. Please set the unit closely to the bone in front of the antilobium

#### 1. Description of each section and bundled items

#### 2. Before use

- ① Confirm power is charged
- ② Set a safety strap to a unit to prevent it from falling
- 3 Set a unit to a mask strap

#### 3. How to use

- 1) Setting
- ② Switching transmitting and receiving
- ③ Speaking/Hearing
- 4 Turning OFF the power
- 4. Maintenance after diving
- 5. How to charge
- 6. Tips for help

Please make sure to read the Instruction Manual attached for the detail specification and trouble

#### ② Switching transmitting and receiving

Logosease starts up with receiving mode when turning the power ON.Speak short vowel sound strongly as "E!(i)" to change the mode to transmitting mode. If you don't speak anything for 3 sec,. the mode will change to receiving mode.






#### 1. Description of each section and bundled items

#### [Description of each section]





#### [Bundled items]



## Refer to [5. How to charge] on the back page for more information.


pink LED is ON

CASIO

#### 3 Speaking/Hearing

[Communication flow]

Or you can tap once the side of the Logosease to switch the mode to/from receiving and transmitting,



What do you need to get accustomed to speaking with a regulator in a mouth?

In the beginning, reading attached speech training sheet, please make sure to practice speaking with a regulator in a mouth.

The more you speak, the better you speak.

Receiving mode

yellow LED is blinking

CASIO


4 Turning OFF the power

the unit out of water.

Power will be OFF automatically in 1 minute after bringing

(The sound of pi, pi, pi, pi, peep, peep, peep, peep will be


# Transmitting mode





# 2 Set a safety strap to a unit to prevent it

Move a strap tie at the right side of mask strap to the buckle side.



#### 3 Set a unit to a mask strap

the mask strap you use.



Set a strap (the other side of setting at the unit) at the right side of

#### × Wrong setting Do not set a unit on the left side

of the mask strap. Set it on the right side.

Set a clip of the unit at the mask strap. Set it to the end of

the clip to prevent the unit from coming off.



## 4. Maintenance after diving

2. Before use

status by the color of LED.

1) Confirm power is charged

the detecting sensor wet in the water.

Power will be ON automatically by getting

Then LED will be blinking to indicate battery

status for 2 seconds. Check the battery

1) Wash the unit with pure water to wash sea water and dirt away after diving for a day

\* Do not wash with detergent. When USB terminal is dirty, clean it with brush.



2 Dry the unit with dried cloth.



fully charged.

blue


battery is enough for about one shot diving.

red

You need charge battery

## 5.How to charge

1) Connect USB cable to the battery charger and PC. (or commercially available USB-AC adaptor)



②Set the unit at the battery charger. Push it until you hear the "click".





(red LED is ON)

(LED is OFF)

## 6. Tips for help

If communication condition is not good (can not hear the transmitted voice well), please check below.

## ■ Check the unit setting position (transmitting side)

Refer [3. How to use] for the correct setting position and setting way



XA unit covers over XA unit is set too law. XA unit is set at

#### ■Check diving environment.



\* There are barriers as rocks between divers.

#### ■Check a unit.

an antenna.



X Air bubbles are attached at

Remove them.



\* Exhausted air bubbles touch the unit.

Incline your head to right to avoid bubble touching the unit as much as possible while

Please make sure to read the Instruction Manual attached for the detail specification and trouble shooting.





